

INNCOM CHM-S

ELECTRONIC DOOR CHIME

The Honeywell INNCOM Electronic Door Chime (CHM-S) is part of the Integrated Room Automation System (IRAS). It works with INNCOM System-5 (S5 bus) guestroom controls, serving as a doorbell chime that announces visitors to the guestroom when the corresponding button is pressed on a doorplate outside the room.

The CHM-S works with INNCOM INNtouch guest annunciation devices (including MODEVA and Designer Series INNtouch-compatible devices). It may also be retrofitted to work with preexisting doorbell systems.

The Electronic Door Chime sounds only once when its button is pressed, and its sound level is set at a volume that prevents guests in adjacent rooms from hearing it.

Guests can also disable the chime using the "Privacy" feature on an in-room INNtouch device.

The CHM-S is mounted in the entry area of the guestroom and connects directly to the X05B driver or similar device through a 3-conductor low-voltage cable. Recommended mounting areas are in a closet, or in the return air duct of the air conditioning system, or other such areas where it can be heard in the room.



CHM-S Electronic Door Chime



Enhances guest privacy and satisfaction



Adjustable volume level



Mechanical mounting ready

Honeywell

INNCOM CHM-S ELECTRONIC DOOR CHIME

CHM-S SPECIFICATIONS	
PART NUMBER	04-1038
DIMENSIONS	2.75"W x 4.68"H x 2.125"D (70mm x 119mm x 54mm)
AUDIO CAPABILITIES	1.0W speaker, 8 OHMS
INPUT VOLTAGE	Requires 12VDC, supplied by INNCOM room controller

For indoor use only

For more information
inncom.com

Honeywell Hospitality
12 Clintonville Road
Northford, CT 06472
1-800-543-1999

IN-DT-CHM-S-Chime | 01-00253 | 2021-08-03
© 2021 Honeywell International Inc.

Honeywell